

Datasheet for: ASF3000EU

Product Type: Advanced Filter Balanced Power Supply

3000VA 230v to 230v CTE with Schuko to C19 input lead, five UK sockets with Schuko adaptors & Avery Magnetics Advanced Filter System.

| | |
|--------------------|--|
| VA | 3000 |
| Input Voltage | 230 |
| Input Termination | 16A IEC Chassis Connector |
| Input Current | 13 |
| amps | 13 |
| Output Voltage | 230 |
| Output Termination | Five UK 13amp 3pin sockets with Schuko adaptors. |
| Product Case | ASF Black Steel Powdercoated Case |
| Dimension | Ht:125 W:230 L:315 |
| Weight | 24kg |
| Primary Protection | Push to reset thermal circuit breaker SP12 |
| Surge Protection | Relay controlled limiter in Avery filter |
| Product Type | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |
| Notes | Fitted with Avery Magnetics Advanced High Current Filter with inter-winding copper foil screen & 2 pole illuminated on/off switch. |



Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product ASF3000EU conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
18/12/2025



www.airlinktransformers.com - VAT No. 573 1888 10
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com