

Datasheet for: EU-JACBS1000

Product Type: Conditioning Balanced Power Supply

1000VA 230V to 100V CTE Two Japan 3 pin sockets with Schuko mains lead.



VA	1000
Input Voltage	230
Input Termination	Mains lead with Schuko plug
Input Current	4.34
amps	15
Output Voltage	100
Output Termination	Two Japanese 3pin sockets
Product Case	USL2 Grey powder coated Steel case
Dimension	Ht:120 W:190 L:260
Weight	8kg
Primary Protection	Push to reset circuit breaker SP8
Surge Protection	SL32 Surge Limiter
Product Type	Safety Isolating transformer
Standard	Conforms to EN61558-2-6 CE & RoHS
Notes	IEC Inlet 2-pole switch with Line filter & EMC Shield

Commodity code: 851539130

RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product EU-JACBS1000 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin.
21/06/2025



www.airlinktransformers.com - VAT No. 573 1888 10

Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS
01279 431865 | sales@airlinktransformers.com