

Datasheet for: SL0301

Product Type: Halogen Lighting Transformers

300VA 230v to Single 12v

| VA | 300 |
|----------------------|------------------------------------|
| Input Voltage | 230 |
| Input Termination | Screw terminals with fuse |
| Input Current | 1.3 |
| amps | 25 |
| Output Voltage | 12 |
| Output Termination | 2way screw terminal |
| Product Case | SL100 White steel case |
| Dimension | Ht:70 L:230 W:140 (mm) |
| Weight | 4kg |
| Primary Protection | Glass fuse |
| Secondary Protection | SP30 Push to reset circuit breaker |
| Surge Protection | SL15 Surge Limiter |
| Product Type | Safety Isolating Transformer |
| Standard | Conforms to EN61558-2-6 CE & RoHS |



Declaration of Conformity: Airlink Transformers declare that the product SL0301 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 21/06/2025

www.airlinktransformers.com - VAT No. 573 1888 10 Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478 14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS 01279 431865 | sales@airlinktransformers.com



RoHS Certificate: Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

