# AIRLINK TRANSFORMERS



# Datasheet for: SL0401

## Product Type: Halogen Lighting Transformers

400VA 230v to Single 12v

| | |
|---|---|
| VA | 400 |
| Input Voltage | 230 |
| Input Termination | Screw terminals with fuse |
| Input Current | 1.739130434782609 |
| amps | 33.333333333333 |
| Output Voltage | 12 |
| Output Termination | 2way screw terminal |
| Product Case | SL500 White steel case |
| Dimension | Ht:90 L:290 W:155 (mm) |
| Weight | 5kg |
| Primary Protection | Glass fuse |
| Secondary Protection | SP45 Push to reset circuit breaker |
| Surge Protection | SL15 Surge Limitor |
| Product Type | Safety Isolating transformer Conforms to EN61558-2-23 CE & RoHS |

**Commodity code:** 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)

**Declaration of Conformity:** Airlink Transformers declare that the product SL0401 conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin.
05/05/2025