

## Datasheet for: UK-JA4200HW

## **Product Type: Use Japanese Appliances in The UK**

4000va 230v to 200v Voltage Convertor Hardwired



| VA                 | 4000   |
|--------------------|--|
| Input Voltage      | 230  |
| Input Termination  | Screw terminal 3way                                      |
| Input Current      | 17   |
| amps               | 20   |
| Output Voltage     | 200  |
| Output Termination | Screw terminal 3way                                      |
| Product Case       | P5 Grey steel case Wall/Floor mounting                   |
| Dimension          | Ht:353 L:350 W:242 (mm)                                  |
| Weight             | 23kg   |
| Primary Protection | Push to reset circuit breaker SP12                       |
| Product Type       | Autowound transformer Conforms to EN61558-2-13 CE & RoHS |

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ethere Difenil Polybromurate (PEDE)



Declaration of Conformity: Airlink Transformers declare that the product UK-JA4200HW conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

Declaration by the Exporter: The exporter of the product covered by this document declares that these products are of EU preferential origin. 05/05/2025

www.airlinktransformers.com - VAT No. 573 1888 10 Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478 14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS 01279 431865 | sales@airlinktransformers.com