



## Datasheet for: UK-US5120NEMA

### Product Type: Use American Appliances in The UK

5000VA 230V to 240V (2x120V) with Nema 14-30R Output Connector



VA	5000
Input Voltage	230
Input Termination	Screw terminals
Input Current	22
amps	50
Output Voltage	240
Output Notes	Supplies 2 x 120V out of phase via Nema 14-30R connector to give total 240V for large US appliances. Optional L14-30R socket available.
Output Termination	Nema 14-30R US Large Appliance Connector
Product Case	P5 Industrial floor/wall mounting case IP23
Dimension	Ht:353 L: 350 W:242 (mm)
Weight	35kg
Primary Protection	MCB 25A 2P
Secondary Protection	2 x 32A MCB
Surge Protection	MS35 Surge Limiter
Product Type	Safety Isolating transformer
Standard	Conforms to EN61558-2-6 CE & RoHS
Notes	Available in hard wired format for installation in RV etc.
Fixing	Floor/Wall mount

Commodity code: 851539130

**RoHS Certificate:** Airlink Transformers certifies and testifies that all the products and goods delivered and invoiced, do not contain any of the hazardous substances as mentioned in the 2011/65/EU European directives (RoHS). Particularly these products do not contain: Heavy metals such as Pb, Cd, Cr6+ Bifenil Polybromurate (PBB) Ether Difenil Polybromurate (PEDE)



**Declaration of Conformity:** Airlink Transformers declare that the product UK-US5120NEMA conforms to current European safety and EMC regulation EN61558-2-6 (Safety Isolating transformer) CE & RoHS compliant. Manufactured to Class A 105degC.

**Declaration by the Exporter:** The exporter of the product covered by this document declares that these products are of EU preferential origin. 15/04/2026



www.airlinktransformers.com - VAT No. 573 1888 10  
Airlink Transformers is a trading name of Albury Services Ltd company reg No 2666478  
14 Capital Place, Lovet Road, The Pinnacles, Harlow, Essex, UK, CM19 5AS  
01279 431865 | sales@airlinktransformers.com